



Ratchet Crimp Tool complete with die set for terminating COAX 75 ohm BNC, Micro BNC and DIN 1.0/2.3 suitable connectors to Canford group X, Y broadcast cables as well as Canford SDV-F-HD. Belden 1855A applications using EF size connectors can also be accommodated. Die set has the following cavities:

0.95mm	(0.037") A/F Square for centre contact
1.07mm	(0.042") A/F Square for centre contact
1.72mm	(0.068") A/F Hexagon for centre contact
5.41mm	(0.213") A/F Hex
8.23mm	(0.324") A/F Hex

Jaws can be reversed for left handed use.

Note that this tool may not be suitable for other brands of 75 ohm BNC, Micro BNC and DIN 1.0/2.3. Check die cavities required for your chosen connector.

#### Suitable Connectors:

<b>BNC-12G</b>	48-5061 COAX CONNS 10-005-W126-FA BNC 12G UHD Male cable, black, group X 48-5071 COAX CONNS 10-005-W126-FA BNC 12G UHD Male cable, black, group X (pack of 100) 48-5063 COAX CONNS 10-005-W126-FC BNC 12G UHD Male cable, black, group Y 48-5073 COAX CONNS 10-005-W126-FC BNC 12G UHD Male cable, black, group Y (pack of 100) 48-5070 COAX CONNS 10-005-W126-FF BNC 12G UHD Male cable, black, Canford SDV-F-HD 48-5080 COAX CONNS 10-005-W126-FF BNC 12G UHD Male cable, black, Canford SDV-F-HD (pk of 100)
<b>BNC-12G RA</b>	48-5081 COAX CONNS 10-104-W66-FA BNC 12G UHD Male cable, right-angle, black, group X 48-5091 COAX CONNS 10-104-W66-FA BNC 12G UHD Male cable, r/angle, black, gp X (pack of 100) 48-5082 COAX CONNS 10-104-W66-FC BNC 12G UHD Male cable, right-angle, black, group Y 48-5092 COAX CONNS 10-104-W66-FC BNC 12G UHD Male cable, r/angle, black, gp Y (pack of 100)
<b>BNC-3G</b>	48-5044 COAX CONNS 10-005-B36-1-AB BNC 3G HD Male cable, group J 48-5054 COAX CONNS 10-005-B36-1-AB BNC 3G HD Male cable, group J (pack of 100) 48-5043 COAX CONNS 10-005-B36-FC BNC 3G HD Male cable, group Y 48-5053 COAX CONNS 10-005-B36-FC BNC 3G HD Male cable, group Y (pack of 100)
<b>BNC-12G Female</b>	48-5087 COAX CONNS 10-054-D126-FA BNC 12G UHD Female cable, group X 48-5097 COAX CONNS 10-054-D126-FA BNC 12G UHD Female cable, group X (pack of 100)
<b>MICRO BNC-12G</b>	48-5022 COAX CONNS 67-005-B66-FA MICRO BNC 12G UHD Male cable, group X 48-5032 COAX CONNS 67-005-B66-FA MICRO BNC 12G UHD Male cable, group X (pack of 100)
<b>DIN 1.0/2.3-12G</b>	48-5002 COAX CONNS 52-005-B6-FA DIN 1.0/2.3 12G UHD Male cable, group X 48-5012 COAX CONNS 52-005-B6-FA DIN 1.0/2.3 12G UHD Male cable, group X (pack of 100)
<b>DIN 1.0/2.3-3G</b>	48-5003 COAX CONNS 52-005-B6-EF DIN 1.0/2.3 3G HD Male cable, Belden 1855A 48-5013 COAX CONNS 52-005-B6-EF DIN 1.0/2.3 3G HD Male cable, Belden 1855A (pack of 100) 48-5006 COAX CONNS 52-005-B6-FC DIN 1.0/2.3 3G HD Male cable, group Y 48-5016 COAX CONNS 52-005-B6-FC DIN 1.0/2.3 3G HD Male cable, group Y (pack of 100)